

# SENZA™ PRIME

## C573R-13” RECUMBENT CYCLE

The SENZA™ Prime line encompasses our quality cardio products, integrated with premium technology and entertainment options that actively engages users by providing an intuitive workout experience that allows them to consume their entertainment, their way. The C573R-13” Recumbent Cycle features an easy step-through design for ease-of-access, adjustable seat and an integrated 13-inch SENZA™ display.



### KEY FEATURES

- 13-inch SENZA™ touchscreen
- Adjustable seat
- Contact HR sensors

| TECHNICAL DETAILS         |  |
|---------------------------|--|
| <b>Unit Weight</b>        | 204.6 lbs / 93 kg  |
| <b>Dimensions (LxWxH)</b> | 69.5 x 24.6 x 55.2 inches / 176.5 x 62.5 x 140.2 cm          |
| <b>Resistance</b>         | 40 Levels  |
| <b>Power Requirements</b> | 120V; 60Hz / 220V; 50Hz                                      |
| <b>Plug Requirements</b>  | Contact your sales rep for specific requirements             |
| <b>Max User Weight</b>    | 400 lbs / 180 kg   |
| <b>Readouts</b>           | Heart Rate, RPM, Resistance, Time, Distance, Speed, Calories |
| <b>Workout Programs</b>   | Manual, Interval, Heart Rate Programs                        |
| <b>Features</b>           | Multi-point seat adjustment<br>Step-through design           |

| TOUCHSCREEN TECHNICAL DETAILS |  |
|-------------------------------|--|
| <b>Screen</b>                 | TFT Backlit LED Capacitive Touchscreen w/ Anti-Glare   |
| <b>Resolution</b>             | 1920 x 1080  |
| <b>Screen Size</b>            | 13 in / 33 cm  |
| <b>Aspect Ratio</b>           | 16:9   |
| <b>Operating System</b>       | Android 5.1.1  |
| <b>Contrast ratio</b>         | 500:1  |
| <b>Processor</b>              | NXP Freescale I.MX6 Quad Core, 1GHz  |
| <b>Memory</b>                 | 32GB eMMC  |
| <b>Languages</b>              | English, Spanish, German, French, Dutch, Italian, Danish, Turkish, Norwegian, Polish, Vietnamese, Chinese (Simplified), Chinese (Traditional), Japanese, Russian, Arabic                               |
| <b>System Updates</b>         | Manual USB or Push (via Wi-fi opt-in)  |
| <b>Brightness</b>             | 15 Adjustable Settings (300 cd/m2)   |
| <b>Viewing Angle</b>          | 160° Vertical & Horizontal   |
| <b>Connectivity</b>           | Wi-fi (IEEE 802.11 a/b/g/n)   LAN Ethernet (10/100Mbps)  |
| <b>Web Browsing</b>           | Closed browser, owner/operator determines web page availability  |
| <b>TV Support</b>             | ATSC / QAM(64,256) / NTSC   DVBT / PAL / SECAM   |
| <b>Inputs</b>                 | AV (CVBS)   Coax   |
| <b>Readouts</b>               | Resistance, Stride length, Time, Heart rate, Distance, Calories, Strides per minute  |
| <b>Workout Programs</b>       | Manual, Random, Interval, Glute, Hill, Track, Fat Burn, Lifestyle, SENZA™ Journey, Heart Rate, Fitness Programs, 5K Trainer  |
| <b>Features</b>               | Bluetooth 4.0 heart rate support<br>Bluetooth-AVRCP iOS & Android music compatible<br>Customizable home screen logo, embedded url on home screen, screen saver images & web pages<br>6 SENZA™ Journeys |